

Field Day Scripts W7FLO

CALLING CQ

1. **Listen first** on frequency to see if anyone else is using it.
 2. Key the microphone and say: "CQ Field Day CQ Field Day CQ Field Day This is Whiskey 7 Foxtrot Lima Oscar Whiskey 7 Foxtrot Lima Oscar QRZ?"
 3. Listen for any response. If a pile up occurs where more than one station responds, listen closely for a call or partial call you recognize and respond: "*<<Full Call Sign of station>>* GO."
 4. The other station will say something like: "Whiskey 7 Foxtrot Lima Oscar this is Whisky One Alpha Whisky please copy five alpha CT. 5A CT QSL" **Add this information to the logging program, then:**
 5. You will respond with: "Whiskey 7 Foxtrot Lima Oscar copied five alpha CT five alpha CT, please copy **2 Foxtrot Oregon 2 Foxtrot Oregon** QSL."
 6. The other station responds: "QSL W7L Whisky One Alpha Whisky have a wonderful Field Day."
 7. You say: "Thanks and 73 W7L." **Stay on frequency and listen for another station trying to contact you and repeat.**
-

RESPONDING TO SOMEONE ELSE'S' CQ

1. When the other station stops calling CQ, say: "Whiskey 7 Foxtrot Lima Oscar." **[Note: Do NOT give the Class and Location at this time.] Listen to see if the other station repeats your call sign as in 3, above.**
 2. If the other station calls you back, your response is: "*<<Full Call Sign of other station>>* this is Whiskey 7 Foxtrot Lima Oscar please copy **2 Foxtrot Oregon 2 Foxtrot Oregon** QSL."
 3. The other station will say something like: "Whisky One Alpha Whisky copied 2 Foxtrot Oregon 2 Foxtrot Oregon, please copy five alpha CT. 5A CT QSL" **Add this information to the logging program, then:**
 4. You respond: "QSL Whisky One Alpha Whisky have a wonderful Field Day. W7L."
 5. The other station say: "Thanks and 73 W1AW." **Tune to the next signal and repeat.**
-